



Industrial Full SFP Switch 10 ports: 8*100M SFP ports, 2*Gigabit SFP ports



Product Description


The KBC ESUMN8-P2-B is a high performance, unmanaged industrial full SFP switch with 8* 100M SFP and 2 *Gigabit SFP ports. Eight 100M SFP ports can connect media converter and other switch which is with 100M SFP ports such as ESULS4-M1-B, 2*Gigabit SFP ports can connect up level switch so that the whole transmission is optics only. The switch is rugged in design with an IP40 enclosure and industrial level 3 ESD protection. Unique mount design makes DIN mounting and removal simple. The rugged design is suitable for use in harsh environment applications, such as Power, Transportation, Pipeline, Petrochemicals, Automation Industries and IP surveillance.



Product Features

- Unmanaged industrial switch
- 8*100M Base-FX SFP
- 2*Gigabit SFP ports
- Redundant Power supply input
- Overload current protection and reverse polarity protection
- Level 3 ESD protection
- IP40 housing design
- Supporting DIN rail or wall-mounted
- Unique DIN mount design makes mounting and removal simple

Typical System Configuration



Specifications

Standards

IEEE Standards IEEE802.3, IEEE802.3u IEEE802.3ab, IEEE802.3z

Ports

100MBase-FX SFP 8 1000Base-FX SFP⁽¹⁾ 2

Switch Performance

Architecture Store-and-forward

Buffer 1M
MAC Address 8K
Switch Capacity 5.6GGbps

Mechanical

Dimension (W×D×H) 68mm × 105mm × 146mm

Weight 0.9k

Power (2)

Redundant Power Input 12 ~ 24Vdc
Power Consumption < 8W
Overload Current Protection Yes
Reverse Polarity Protection Yes

Protection


Enclosure IP40 ESD Industrial level 3


Environmental

Operating Temperature $-40^{\circ} \sim +75^{\circ}C$

Storage Temperature -40° ~ +85°C

Operating Humidity 5% to 95% non-condensing





Order Information

ESUMN8 - P2 - B: Unmanaged, 8*100M Base-FX SFP, 2*1000MBase-FX SFP

- 1. SFP module sold separately.
- 2. Power supply sold separately.

Due to ongoing technological improvements, product specifications are subject to change without notice. KBC is not liable for any errors, omissions or changes of any description of the goods contained herein. This information is for the sole purpose of identifying the products and KBC makes no warranty that the products conform to any description contained herein. Do not rely solely on any representations, statements, or assertions concerning these Products contained herein.